

Förberedelser:

- Rengör kanten på solskyddet med exempelvis T-sprit eller isopropanol för att få bort eventuella rester av smuts, fett och vax.

Montering och installation:

1. Dra av skyddsplasten på Arc/Arc+ LED-listen och tryck fast denna på solskyddets kant
2. Montera de medföljande klämfästena i ändarna av listen
3. Borra ett hål genom solskyddets kant för kabeln till strömmatningen
4. Led in kabeln genom samma gummigenomföring som kepsbelysningen samt koppla in LED-listen
Inkoppling görs valfritt antingen över positionsljus, tändningen (säkring 108) eller en separat strömställare

Inkoppling:

Arc toppskyltsbelysning

Vitt eller Orange Ljus

47122163 / 47122161

Röd: 24V DC "+" (Vitt eller orange ljus)

Svart: Jord "-"

Arc+ toppskyltsbelysning

Vitt och Orange Ljus

471223231



Röd: 24V DC "+" (Vitt ljus)

Svart: Jord "-"

Gul: 24V DC "+" (Orange ljus)



Varning!

- Använd endast under angiven spänning (DC 24V)

Preparations:

- Clean the edge of the sunshade with, for example, denatured alcohol or isopropanol to remove any residue of dirt, grease, and wax.

Assembly and Installation:

1. Remove the protective film from the Arc/Arc+ LED strip and press it onto the edge of the sunshade.
2. Mount the included clip brackets at the ends of the strip.
3. Drill a hole through the edge of the sunshade for the power cable.
4. Thread the cable through the same rubber bushing as the cap lighting and connect the LED strip.
The connections can be made either via the position lights, the ignition (fuse 108), or a separate power switch.

Connection:

Arc Top Sign Light White or Orange light

47122161 / 47122163

Red: 24V DC "+" (White or orange light)
Black: Ground "-"



Arc+ Top Sign Light White and Orange light

471223231



Red: 24V DC "+" (White light)
Black: Ground "-"
Yellow: 24V DC "+" (Orange light)

Warning!

- Use only under the specified voltage (DC 24V)